
All in one solar street/garden light (20W)				
Solar panel	Max power	18V 40W (high efficiency monocrystalline silicon)		
	Life time	25 years		
Battery	Туре	12.8V 18AH(Lithium iron phosphate Battery); brand:mottcell		
	Life time	5 years		
LED Lamp (with sensor)	Max power	12V 20W		
	Led chip brand	Bridgelux from USA with high brightness		
	Lumen (LM)	2500-2600lm (125-130lm/w)		
	Life time	50,000hours		
	Viewing Angle	120°		
Controller	specifications	12V 10A MPPT intelligent controller,light and time control,auto ON/OFF Overload Protection;Over Charging Protection;Over Discharge protection Short circuit protection;Anti reverse polarity protection Cutting off by itself;Anti pouring charge;Anti thunder		
Accessories	For installation	Installation bracket/Nuts/Bolts		
Charge time	By sun	7 hours (with enough strong shine)		
Discharge time	Full power	more 20 hours		
	Saving mode	more 40 hours		
Working Temperature	Range( ℃ )	-30℃~+70℃		
Colour temperature	Range(k)	6000-7500k (can customized)		
Mounting height	Range (m)	5-6m		
Space between light	Range (m)	18-20m		
Lamps material of main Aluminium alloy				
Certificate	CE / ROHS / IP65			
Warranty period	2 years	ars		
Packing & Weight	Product size	920*330*140mm	Carton size	950*410*210 mm
	Product weight	12.5kg	GW.for carton	15 kg
	Packing box	neutral	Q'ty/ctn	1sets/ctn
Packs Containers	20' GP	375sets	40' GP	792sets

## Remark:

- 1. Sample Price and Wholesale Price in this offer are based on EXW price, not including shipping costs, tax and duties;
- 2. More quantity, more discount;
- 3.Payment method: T/T 100% or Western Union 100% Under USD30,00, 30% Deposit and 70% before delivery for more than USD 30,00;
- 4. Quotation validity: 20 days.





**Applications** 



- 1,All in one solar street light centralize a high-efficiency solar panels, 5 years long-life Lithium iron phosphate Battery, high luminous efficiency of LED and intelligent controllers, motion sensor, anti-theft mounting brackets into one solar street light.
- 2,The benefits of all in one solar street light is easy to install, light weight, usually two workers can complete the installation only with a wrench in 5 minutes, neither the use of heavy equipment or tools, nor technical support or engineers's guidance.